

14. The Developer shall submit to the City Engineer, and Street Department for approval, prior to installation, six (6) copies of drawings on the following items:
  1. Manufacturer's Drawings
    - a. Light Fixture
    - b. Pole and Arm
    - c. Lamps
    - d. Combination lighting contactor and cabinet
    - e. Cable
    - f. Photocontrol
  2. Specification
  3. Engineered Drawings
15. The Developer is referred to the Standard Construction Drawings, "Lighting Assembly", "Light Standard Base Detail", "Pole Detail", "Alternate Residential Luminaire/Pedestal Pole Detail", and "Service Structure for Street Lighting" as part of this Specification.
16. Street Department shall receive one (1) complete set of manufacturers approved submittal drawings.
17. Final inspection shall be coordinated with the Street Department.
18. Where "Approved Interchangeable Equal" is called for in these Specifications it shall be construed to mean that parts will be interchangeable with the parts called for without the need for any modifications or adaptive devices. Approval shall be by the City Engineer and the Street Department for Reynoldsburg, Ohio.
19. Developer to furnish City with surplus materials in accordance with the following:

# of Light Pole Installations	Surplus Materials			
	Globes	Globes	Luminaires	Globes
1-10	1	1	1	1
11-20	2	2	2	2
21-30	3	3	3	3
31-40	4	4	4	4
41-50	5	5	5	5
Etc.				

NOTE: For every new Control Site (service structure) in the project, the first pole from the above schedule shall be complete with photocell.

After Construction: The Developer shall be required to provide a cash maintenance bond equal to five percent (5%) of the total cost of the street light installations. Such amount shall be deposited at the time energization is requested, and shall be used by the City to perform necessary repairs during a 1-year Developer maintenance period following energization and burn test. Should the amount be insufficient to cover all repairs required during this period, additional monies shall be deposited. In the event that all funds are not expended, the unused balance shall be returned to the Developer without interest.

The maximum number of street lights to be connected to any one controller shall be 35.

	<b>STREET LIGHTING SPECIFICATIONS</b>	<b>CITY OF REYNOLDSBURG, OHIO</b>	
		<b>STANDARD CONSTRUCTION DRAWING</b>	
		Rev. 01-16-01	Date 06-05-91